

NAVnet
TZ2
touch

**IF-NMEAUI Software
Update Procedure
Using TZT2**

Preperation for IF-NMEAFI Software update


1. USB memory (Do not use SD to USB Adapter)



2. Download IF-NMEAFI Software for the TZT2 from the Furuno USA website under the “Software” selection of the IF-NMEAFI product page.

3. Unzip IF-NMEAFI Software

4. Move unzipped software contents to root of USB memory. Root of USB memory will contain the following only:




(Note: When you open your USB memory window, you should see only the files shown above. They should not be changed or placed inside any additional folders. Other software, photos, or files should NOT be on the USB along with this upgrade software)

5. With the power off to the MFD. Insert USB memory into the USB pigtail cable located on the back of the TZT2 MFD. This will be a white pigtail cable. Power on the TZT2 MFD and boot up normally.

You are now ready to begin the IF-NMEAUI software update

1. Press **Home** Button




2. Press **Settings**




3. Press Initial Setup




4. Press Update Network Equipment



5. If IF-NMEA2K2 is not recognized Press **Scan**




6. Make sure the Update Box is checked for IF-NMEA2K2 then press **Start** and acknowledge the update to begin the Update process.



7. You will be notified once the update process is finished.

Press **Ok** and then press **Exit**



The unit will reboot back to normal mode. You may now remove the USB memory.

How to verify IF-NMEA2K2 has been successfully updated.

1. Access the **Initial Setup** menu. Press **Sensor List**



2. Verify that the updated software version is displayed.
(Other device v1.16 is shown in this example)

NETWORK SENSOR					
Name	NickName	Version	IP	HostName	
TZTL15F (Me)	TZTL15F	06.21:06.21:06.23:	172.031.252.001	MF252001	
CAN BUS SENSOR					
Name	NickName	Version	Instance		
IF-NMEA2K2	IF-NMEA2K2	01.16:01.01	0		